

FNK 10 CARDIOID CONDENSER MICROPHONE

- The FNK 10 gooseneck – mounted is a professional condenser microphone designed primarily for speech and vocal pickup.
- They can be mounted on lecterns, pulpits, conference tables and much more.
- Single gooseneck section near microphone base for easy orientation of the microphone.
- XLR connector with phantom power or two double A batteries can bring power for the red LED ring and the microphone signal.
- Streamlined design for seamless integration, the gooseneck's slender design is far less obstructive than a traditional microphone setup.
- Includes foam windscreen to prevent unwanted noise.



XLR Cable



Status LED



Ultra flexible neck



XLR Socket



Code: 600203

SPECIFICATIONS

Type: Condenser	Directivity: Directional (Cardioid)
Frequency response: 60Hz – 18KHz	Max SPL: 128dB (1 KHz)
Output impedance: 600 Ohm	S/N rate: 63dB
Sensitivity: -56dB +/- 3dB	Dynamic range: 99dB
Battery: 3V DC	

FEATURES

- Cardioid polar pattern for easy adaption to any situation
- Condenser microphone
- Easy to assembly with battery support
- On/Off switch
- Status LED
- Cable included
- Strong and stable support

PACKING INFO

MASTER DIMENSIONS: 450X410X415 MM / 17.7X16.1X16.3 IN
GROSS WEIGHT: 10.6KG / 20.27 LB MASTER PIECES: 10 PCS